

# XDL Series

## 19 Inch Rack Mount Kit

### RM-XDL

The RM-XDL is designed to accommodate up to three single XDL power supplies or combination of a triple and a single output unit. Blanking pieces are included for unused positions in the rack. It is recommended that side supports, e.g. telescopic slides, are used with the rack as the power supplies are heavy. The rack should be drilled and assembled with the side supports before the power supplies are fitted to the rack.

#### **Installation Instructions**

Turn the XDL power supply to be installed into the rack mount upside down so that they are lying on their top face. If there are multiple power supplies to be installed, lay them side by side. Remove the four screws in each power supply which hold the feet; the screws which retain the front tilting feet are accessed by first removing the self-adhesive rubber insert in the molded foot.

Without removing the case covers, overlay the rack mount over the power supplies with the front edge aligned with the outside of the front panel molding. The screw holes for the feet should line up with the recessed holes in the rack. Secure the power supply to the rack using the same screws that held the feet. Fit the blanking piece, if required, using the screws supplied. Turn over the rack mount fitted with power supplies to the upright position. The rack mount fitted with the XDL is now ready for installation to the rack cabinet.

Ensure that there is adequate forced cooling in the rack close to the power supplies. Refer to the XDL manual for the temperature operating range.